


MatixGo Connected 2 ways switch

JW4003C - JG4003C - JB4003C



Use

The connected 2 ways switch allows to control lights locally or remotely. The connected 2 ways switch has the same installation and usability of a traditional 2 ways switch and it is compatible with all loads with max power 250W. It is equiped with a blue LED light used always on for localization modality or on, when the ight in on for the load status modality. It can be associated with "wireless light switches".

Caution: must be connected to the neutral. - 1 module.

Range Designation Cat. Nos. Connected switch for lighting. □ JW4003C Equipped with an LED indicator. □ JG4003C Hidden reset button used to return to factory settings. ■ JB4003C

Black

Connection

Colours code:

Terminal type: screw

☐ White ■ Grey

Terminal capacity: 1 x 2.5 mm² - 2 x 1.5 mm²

Stripping length: 7 mm
Screwdriver: 3 mm flat

Technical characteristics

- Mechanical characteristics

Protection against impacts: IK 04

Protection against solid bodies/liquids: IP 20 assembled product

- Material characteristics

Mechanism casing: PC Halogen-free

UV resistant

Self-extinguishing: $+850^{\circ}$ C/30 s for insulating parts holding live parts in place.

+650°C/30 s for the other insulating components.

- Electrical characteristics

Voltage: 100/240 V~
Current: 2 A max bulb
Current: 0,4 A max LED
Current: 1 A max CFL
Frequency: 50/60 Hz
Standby consumption: 1 mA

Zigbee technology 2.4 GHz to 2.4835 GHz Power level: REC 70-03: < 20 dBm

Range: 200 m of unobstructed space

10 m between products

- Climate characteristics

Storage temperature: $0^{\circ}\text{C to } +45^{\circ}\text{C}$ Usage temperature: $+5^{\circ}\text{C to } +45^{\circ}\text{C}$

Standards and approvals

Compliant with installation and manufacturing standards.

See e-catalogue.

The undersigned, BTICINO, declares that the radio-electric equipment type (JW4003C-JG4003C-JB4003C) complies with directive 2014/53/EU.


The full text of the EU declaration of conformity is available on the following website: www.bticino.it/red


/ww.bucino.it/reu



MatixGo Connected 2 ways switch

Overall dimensions (mm)







Α	В	C	D	
45	22,5	37	7,6	

Operation

Front view



Front view without coverkey



Legend

- 1. Control Pushbutton
- 2. LED indicator: useful during installation
- 3. RESET pushbutton: used to return to factory settings

Cleaning

Clean the surface with a cloth.

Do not use acetone, tar-removing cleaning agents or trichloroethylene. \\

Caution: Always test before using special cleaning products.

The plates must not be painted.



